

## 8U Adjustable Depth Open Frame Wall Mount Equipment Rack

RK812WALLOA

DE: Bedienungsanleitung - de.startech.com

FR: Guide de l'utilisateur - fr.startech.com

ES: Guía del usuario - es.startech.com

IT: Guida per l'uso - it.startech.com

NL: Gebruiksaanwijzing - nl.startech.com

PT: Guia do usuário - pt.startech.com

### Packaging Contents

- 8U Open Frame Wall Mount Rack Components
- Assembly Hardware (16 Screws)
- 16x M5 Screws and Cage Nuts



\*actual product may vary from photos

### Installation

1. To adjust the depth of the rack, remove the nuts holding the silver Truss-head screws from the sides and top/bottom, then slide the front and rear sections of the rack apart. Set to the desired depth, then re-install the silver Truss-head screws.
2. To affix the RK812WALLOA to a wall, there are 4 anchor points on the rear of the rack. Please use the appropriate screws or bolts for mounting heavy equipment to your specific type of wall. Please observe proper safety procedures and use the appropriate tools.
3. To install rack mountable equipment into the RK812WALLOA, use the provided square cage nuts to provide the mounting points, then use the provided cabinet screws to secure the equipment to the cage nuts.

### Specifications

<b>Description</b>	8U Open Frame Wall Mount Rack- Adjustable Depth
<b>Material</b>	SPCC (2.0mm)
<b>Color</b>	Black
<b>Internal Mounting Height</b>	8U
<b>Maximum Weight Capacity</b>	80 kg
<b>Min/Max Mounting Depth</b>	12in / 20in
<b>External Dimensions (HxWxD)</b>	495.0mm x 535.0mm x 335.0 / 510.0mm
<b>Net Weight</b>	10.82kg
<b>Standards</b>	EIA-310D
<b>Certifications</b>	UL/CE/RoHS

## FCC Compliance Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

## Use of Trademarks, Registered Trademarks, and other Protected Names and Symbols

This manual may make reference to trademarks, registered trademarks, and other protected names and/or symbols of third-party companies not related in any way to StarTech.com. Where they occur these references are for illustrative purposes only and do not represent an endorsement of a product or service by StarTech.com, or an endorsement of the product(s) to which this manual applies by the third-party company in question. Regardless of any direct acknowledgement elsewhere in the body of this document, StarTech.com hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders.

## Technical Support

StarTech.com's lifetime technical support is an integral part of our commitment to provide industry-leading solutions. If you ever need help with your product, visit [www.startech.com/support](http://www.startech.com/support) and access our comprehensive selection of online tools, documentation, and downloads.

For the latest drivers/software, please visit [www.startech.com/downloads](http://www.startech.com/downloads)

## Warranty Information

This product is backed by a lifetime warranty.

In addition, StarTech.com warrants its products against defects in materials and workmanship for the periods noted, following the initial date of purchase. During this period, the products may be returned for repair, or replacement with equivalent products at our discretion. The warranty covers parts and labor costs only. StarTech.com does not warrant its products from defects or damages arising from misuse, abuse, alteration, or normal wear and tear.

## Limitation of Liability

In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product. Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.