

Navilock NL-8004P MD6 Serial PPS Multi GNSS Receiver u-blox 8 5 m

Description

The MD6 serial multi GNSS Receiver based on u-blox 8 chipset has a built-in antenna for high sensitivity. You can use this GNSS Receiver with a notebook and a suitable routing software for navigation. The MD6 universal connector enables the connection of optional USB or serial connecting cables. The NL-8004P GNSS receiver can be installed onto different vehicle roofs (car, truck, bus etc.) by using the included installation material. Thus it can perfectly fit into the vehicle concept, due to its design.



Specification

- Connector:
MD6 Navilock plug (USB or serial cable are optional available)
- u-blox 8 UBX-M8030-KT chipset
- Frequency:
GPS: L1, 1575.4200 MHz
GLONASS: L1, 1602.5625 ~ 1615.5000 MHz
BEIDOU COMPASS: B1, 1561.0980 MHz
GALILEO E1, 1575.4200 MHz
QZSS L1, 1575.4200 MHz
- Accepts the signals of up to 72 satellites at the same time
- Supports AssistNow online/offline, SBAS (WAAS, EGNOS, QZSS and MSAS)
- Supports NMEA 0183 protocols: GGA, GSA, GSV, RMC, VTG
- Auto Baud Rate up to 115200 bps
- PPS signal on pin 6
- Update rate:
single GNSS: 18 Hz (e.g. GPS solo)
multi GNSS: 10 Hz (e.g. GPS+GLONASS)
- Sensibility max. -167 dBm
- IPX7 protection class
- Operating temperature: -20 °C ~ 60 °C
- Cold start in ca. 26 seconds
- Hot start in ca. 1 second
- Positioning accuracy: 2.5 m CEP (Circular Error Probable) and 2 m CEP with SBAS
- Cable length: ca. 5 m
- Dimensions (Ø x H without screw thread): ca. 62 mm x 21 mm

Item No. 62527



EAN	4043619625277
Country of origin	Taiwan, Republic Of China

System requirements

- Windows Vista/7/8/8.1/10, Linux Kernel 2.6
- MD6 connection cable

Package content

- MD6 serial receiver
- Mounting material: stainless steel nut and washer
- Driver CD
- User manual on CD ROM

Package

- Box