

# HP LaserJet 1320 Printer series



HP LaserJet 1320/n/nw  
Printer



HP LaserJet 1320tn Printer

**Designed for professionals or workgroups seeking reliable, space-saving monochrome printing to meet business and personal needs at home or in the office – for fast, high-quality printing, easy connection and sharing, and lower ownership costs.**

#### **Fast printing with up to 21 ppm and instant-on technology.**

- Produce high-quality documents quickly and easily.
- The HP LaserJet 1320 Printers print at speeds of up to 21 ppm.
- Combined with instant-on technology that requires no warm-up time<sup>1</sup>, your prints can be finished before many printers have even started printing.
- With a 133 MHz Motorola V4 Coldfire processor and 16 MB expandable memory, these printers handle even complex files and minimise bottlenecks.
- Selected models allow a total input capacity of 500 sheets, minimising user intervention.

#### **Get professional-looking documents with 1200 dpi.**

- HP LaserJet 1320 Printers keep your performance looking its best.
- Produce professional, high-quality prints every time with true 1200 dpi resolution and high-quality HP printing supplies.
- The results are consistently crisp, sharp and clear.
- Save money and resources with automatic two-sided printing that virtually doubles input capacity and makes paperwork more manageable.

#### **Flexible options to fit your environment.**

- The HP LaserJet 1320 Printer series offers an array of features to give your business the flexibility it needs.
- Share printers across small workgroups with built-in wired or wireless networking<sup>2</sup>.
- Expand printer memory up to 144 MB to handle even complex documents.
- HP Smart Printing technology<sup>3</sup> alerts you automatically when it's time to replenish supplies.
- The compact printer design saves your desktop space.
- Built to fit into your existing office environment, the printer supports a wide range of Microsoft® Windows® or Macintosh operating systems.

<sup>1</sup>First page out less than 8 secs.

<sup>2</sup>HP LaserJet 1320n/nw/tn Printers feature a built-in 10/100 wired Ethernet connection and do not include parallel port connectivity.  
The HP LaserJet 1320nw also features 802.11g wireless networking.

<sup>3</sup>Using genuine HP supplies ensures availability of all HP printing features.

## Technical specifications

<b>Print technology</b>	Monochrome Laser		
<b>Print speed</b>	Up to 21 ppm (A4) First page out: Less than 8 sec. due to instant-on technology (no warm-up time from warm or cold start)		
<b>Processor</b>	133 MHz, Motorola V4 Coldfire		
<b>Memory</b>	16 MB Expandable to 144 MB through 1 industry-standard DIMM slot		
<b>Print quality</b>	True 1200 x 1200 dpi		
<b>Printer languages</b>	HP PCL 5e, HP PCL 6, HP Postscript Level 2 Emulation		
<b>Economical printing</b>	Economode (saves up to 50% toner), immediate return to power-save mode after each print job due to instant-on fuser technology (saves electricity), N-up printing and automatic two-sided printing – duplex (saves paper)		
<b>Typefaces/fonts</b>	HP PCL 6: 45 scalable True Type fonts built-in, HP Postscript Level 2 Emulation: 35 scalable True Type fonts built-in		
<b>Duty cycle</b>	Up to 10,000 pages per month		
<b>Print margins</b>	Top: 4 mm, left: 4 mm, right: 4 mm, bottom: 4 mm		
<b>Media handling</b>	<b>Input</b>	<b>Capacity</b>	<b>Weight</b>
	Priority Tray	Single-sheet multipurpose input slot	60 to 105 g/m <sup>2</sup> , using the standard output bin; 60 to 163 g/m <sup>2</sup> , using the straight through media path
	Standard Tray	Up to 250 sheets	60 to 105 g/m <sup>2</sup>
	Optional Tray	Optional: up to 250 sheets	60 to 105 g/m <sup>2</sup>
	<b>Output:</b> Sheets: up to 125, envelope: 1, transparencies: 100 <b>Duplex printing:</b> Automatic (standard)		
<b>Media types</b>	Plain paper, envelopes, transparencies, cardstock, postcards, labels		
<b>Paper handling</b>	Input: HP LaserJet 1320/n/nw Printer: Single-sheet multipurpose input slot, 250-sheet input tray; HP LaserJet 1320tn Printer: Single-sheet multipurpose input slot, two 250-sheet input trays Output: 125-sheet face down bin, rear output door for special media		
<b>Interface and connectivity</b>	HP LaserJet 1320 Printer: USB port (compatible with USB 2.0 specifications), IEEE 1284-B compliant parallel port HP LaserJet 1320n/ln Printer: USB port (compatible with USB 2.0 specifications), RJ-45 Ethernet 10/100 network port HP LaserJet 1320nw Printer: USB port (compatible with USB 2.0 specifications), RJ-45 Ethernet 10/100 network port, 802.11b/g wireless connectivity Optional: HP Jetdirect External Print Servers; HP Wireless Print Server; HP bt1300, Bluetooth® Print Adapter		
<b>Operating systems compatibility</b>	Microsoft® Windows® 98, Me, NT 4.0 (printer driver only), 2000, XP 32-bit, XP 64-bit (printer driver only), Server 2003, Mac OS 9, OS X v 10.1, OS X v 10.2, OS X v 10.3, MS-DOS, Linux, UNIX® Latest drivers and software available from the HP LaserJet support Web site at <a href="http://www.hp.com/support/lj1320">http://www.hp.com/support/lj1320</a>		
<b>Network operating systems compatibility</b>	Via HP Jetdirect Print Server: Microsoft® Windows® 98, Me, NT 4.0 (printer driver only), 2000, XP 32-bit, XP 64-bit (printer driver only), Server 2003, Mac OS 9, OS X v 10.1, 10.2, 10.3 Optional: Novell® NetWare 3.2, 4.2, 5.x, 6; Red Hat Linux 6.x and later; SuSE Linux 6.x and later; HP-UX 10.20, 11.x; Solaris™ 2.5x, 2.6, 7, 8; IBM® AIX 3.2.5 and later; MPE-iX.		
<b>Minimum system requirements</b>	Microsoft® Windows® 98 and later, Pentium®, 166 MHz, 64 MB RAM Mac OS 9.1 and later, 96 MB RAM, Mac OS X 10.1 and later, 128 MB RAM CD-ROM drive USB port or parallel port		
<b>Standard software</b>	HP printer software on CD-ROM includes HP installer/uninstaller, drivers (HP PCL 5e, HP PCL 6, HP Postscript Level 2 Emulation), HP Toolbox for diagnostic status and configuration, HP Embedded Web Server, control panel simulator, help, documentation		
<b>Control panel</b>	HP LaserJet 1320/n/nw Printer: 3 lights (Toner, Attention, Ready), 2 buttons (Go, Cancel) HP LaserJet 1320nw Printer: 4 lights (Wireless, Toner, Attention, Ready), 2 buttons (Go, Cancel)		
<b>Power requirements</b>	Input voltage 110 to 127 VAC (± 10%), 50/60 Hz (± 2 Hz); 220 to 240 VAC (± 10%), 50/60 Hz (± 2 Hz). Internal		
<b>Power consumption</b>	Active: 345 watts; standby/powersave: 6 watts; off: 0 watt		
<b>Dimensions (w x d x h) (out of package/packaged)</b>	HP LaserJet 1320/n/nw Printer: 350 x 355 x 256 mm/500 x 400 x 498 mm; HP LaserJet 1320tn Printer: 350 x 355 x 344 mm/533 x 493 x 498 mm		
<b>Weight</b> (out of package/packaged)	HP LaserJet 1320 Printer: 10.5 kg/14.06 kg; HP LaserJet 1320/n/nw Printer: 10.5 kg/14.15 kg; HP LaserJet 1320tn Printer: 13.6 kg/18 kg		
<b>Printer management</b>	HP Toolbox, HP Embedded Web Server, HP Web Jetadmin		
<b>Operating environment</b>	Environmental ranges: operating temperature: 10 to 32.5° C, recommended operating temperature: 10 to 32.5° C, operating humidity: 20 to 80% RH, storage temperature: 0 to 40° C, storage humidity: 10 to 80% RH. Noise level per ISO 9296, sound power: LwAd 6.2 B(A), sound pressure: LpAm 55d B(A) printing (operating position), 48d B(A) printing (bystander position)		
<b>Safety</b>	IEC 60950: 1999/EN 60950: 2000; IEC 60825-1: 1993 +A1: 1997 +A2: 2001/EN 60825-1: 1994 +A11: 1996 +A2: 2001 (Class 1 Laser/LED Product); GB4943-2001.		
<b>Certifications</b>	EMC certifications: CISPR 22: 1997/EN 55022: 1998 Class B1; EN 61000-3-2: 2000; EN 61000-3-3: 1995/A1; EN 55024: 1998 FCC Title 47 CFR, Part 15 Class B2)/ICES 003, Issue 3; GB9254-1998, GB17625.1-1998/CNS13438		
<b>Warranty</b>	One-year standard bench repair and return to HP authorised service centre warranty		

\* The HP LaserJet 1320 printer series supports the printing of prescriptions long edge first from the standard and optional paper tray when a Prescription Printing Adapter is fitted.  
The Adapter is available from HP. Please visit [www.hp.com/uk/ppa](http://www.hp.com/uk/ppa) for further details.

<http://www.hp.com/uk>

For more information, please call your local HP sales office or representative: **Austria:** 0800 242 242, **Algeria:** (0)61 56 45 43, **Bahrain:** 800 728, **Belgium:** (078) 15 20 30 (0.0496/min), **Bulgaria:** (+359) 2960 1940, **Croatia:** (+385 1) 60 60 200, **Czech republic:** (00 420) 261 108 108 (Prague), **Denmark:** +45 4812 1000, **Egypt:** 532 5222, **Estonia:** (+372) 6813 823, **Finland:** (+358) 0205 350, **France:** 0 826 800 400, **Germany:** 0180 5 665 775 (Business Products) and 0180 5 652 180 (Consumer Products) (12 Cent/min – fixed network), **Greece:** (01) 678 96 00, **Hungary:** (+36) 1 382-1111, **Iceland:** (354) 570 1000, **Ireland:** + 353 1 6158200, **Israel:** (972) 9-830 4848, **Italy:** (02) 92121, **Kazakhstan:** +7 (3272) 980 824, **Latvia:** 800 80 12, **Lithuania:** 8 800 10000 or +370 5 2103333, **Luxembourg:** (+352) 263 160 34, **Middle East:** 00971 4 883 4427, **Morocco (African Region):** +212 22 40 47 47, **Netherlands:** (020) 5476666, **Norway:** +47 08800, **Poland:** infolinia 0-800 122 622, **Portugal:** 808 206 001, **Romania:** (+401) 205 3300, **Russia:** +7 (095) 797 35 00, **Saudi Arabia:** 800 124 4646, **Serbia/Montenegro:** +381 11 201 99 00, **Slovakia:** +421-2-50222111, **Slovenia:** +386 1 2307 420, **South Africa:** 0800 118 883, **Spain:** (91) 634 88 00, **Sweden:** (08) 444 2000, **Switzerland:** 0848 88 44 66, **Tunisia:** 71 891 222, **Turkey:** +90 (212) 444 71 71, **UAE:** 8004910, **UK:** 08705 474747, **Ukraine:** +380 44 490 61 20.



## Ordering information

<b>Q5927A</b>	HP LaserJet 1320 Printer, power cord, HP LaserJet Print Cartridge, user's guide, printer documentation and software on CD-ROM, single-sheet multipurpose input slot, 250-sheet input tray
<b>Q5928A</b>	HP LaserJet 1320n Printer: as Q5927A plus built-in HP Jetdirect Ethernet 10/100 port
<b>Q5929A</b>	HP LaserJet 1320nw Printer: as Q5927A plus built-in HP Jetdirect Ethernet 10/100 port, built-in 802.11g wireless networking
<b>Q5930A</b>	HP LaserJet 1320tn Printer: as Q5928A plus extra 250-sheet input tray

### Accessories

<b>Q5931A</b>	HP 250-sheet input tray
<b>PPA132001</b>	Prescription Printing Adapter*

### Supplies

<b>Q5949A</b>	HP LaserJet Print Cartridge (2,500 standard pages in accordance with ISO/IEC 19752)
<b>Q5949X</b>	HP LaserJet Print Cartridge (6,000 standard pages in accordance with ISO/IEC 19752)

### Memory

<b>C7842A</b>	HP 8 MB memory DIMM
<b>C7843A</b>	HP 16 MB memory DIMM
<b>C7845A</b>	HP 32 MB memory DIMM
<b>Q1887A</b>	HP 64 MB memory DIMM
<b>C9121A</b>	HP 128 MB memory DIMM

### Connectivity

<b>J3258B</b>	HP Jetdirect 170x External Print Server: Ethernet
<b>J3263A</b>	HP Jetdirect 300x External Print Server: Ethernet/Fast Ethernet
<b>J3265A</b>	HP Jetdirect 500x External Print Server: Ethernet/Fast Ethernet
<b>J7942A</b>	HP Jetdirect en3700 External Print Server: Fast Ethernet
<b>J7951A</b>	HP Jetdirect ew2400 802.11g External Wireless Print Server
<b>J6072A</b>	HP bt1300, Bluetooth® Print Adapter

### Service & support

<b>H2634A/E</b>	HP Care Pack, return to HP, 3 years
<b>H5473A/E</b>	HP Care Pack, next day on-site, 3 years
<b>H3110A/E</b>	Installation & network configuration
<b>U8047PA/PE</b>	HP Care Pack, post warranty, return to HP, 1 year
<b>H2639PA/PE</b>	HP Care Pack, post warranty, next day on-site, 1 year

