



Tripp Lite
1111 West 35th Street
Chicago, IL 60609 USA
Telephone: +(773) 869 1234
E-mail: saleshelp@tripplite.com

Model #: SU2200XLCD

SmartOnline 2.2kVA On-Line Double-Conversion UPS, Tower, Interactive LCD display, 100/110/120/127V NEMA 5-15/20R & L5-20R outlets



Highlights

- 2200VA / 2.2kVA / 1800 watt on-line double-conversion tower UPS
- 100/110/120/127V 50/60Hz output, 97% efficiency economy mode option
- Interactive LCD with 10 selectable screens of UPS and site power data
- Expandable runtime, Hot-swappable batteries
- USB, RS232 & EPO ports, SNMPWEBCARD option
- 2 independently switched load banks
- NEMA 5-20P input; 6 5-15/20R & 1 L5-20R outlets

Description

Tripp Lite Smart Online UPS systems offer high performance power protection ideal for critical server and network equipment in a variety of application environments. Online, double-conversion Uninterruptible Power Supply / UPS maintains perfectly regulated output power by continuously converting raw AC input to DC, then re-converting output back to AC. Sine wave AC output with +/-2% voltage regulation powers network equipment continuously, even during severe brownouts and overvoltages, all without depleting UPS battery reserves. Maintains battery-derived AC output during power failures with zero transfer time. Extended runtime options available. Interactive LCD interface reports UPS operating mode, detailed UPS and site-power data, plus enables a variety of UPS setup and configuration options. Highly efficient operation in optional economy mode saves BTU heat output and energy costs. Network management interfaces support communications via USB, RS-232, contact-closure and optional SNMPWEBCARD network interface. Built-in DB9 port offers both enhanced RS-232 data and basic contact closure monitoring ability. HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Includes PowerAlert monitoring software and complete cabling. Emergency Power Off (EPO) interface. LED display reports UPS operating mode, line power availability, battery mode operation, inverter operation, ECO mode status and output power availability. Audible alarm with push-button momentary alarm-cancel and silent-mode LCD configuration options. Programmable self-test. Fault-tolerant auto-bypass mode. Battery independent restart. Field-replaceable, hot-swappable internal batteries and external battery packs.

Package Includes

- SU2200XLCD UPS System
- PowerAlert Software CD and cabling
- Owner's Manual with warranty information
- EPO (Emergency Power Off) cabling

Features

- Tripp Lite SU2200XLCD 2200VA / 2.2kVA / 1800W on-line, double-conversion tower UPS
- Selectable 100/110/120/127V output (120V factory preset)
- NEMA 5-20P input, 6 5-15/20R & 1 L5-20R outlets
- Two switched output load banks support remote reboot and programmable load shedding options
- Supports 2% output voltage regulation and zero transfer time in double conversion mode
- Economy mode option offers high 97% efficiency, reduced power consumption and lower BTU emissions
- 13 minutes runtime at 50% load (900W) and 4.5 minutes at 100% load (1800W) with internal batteries
- Extended runtime options available with BP48V24-2U (limit 1) or BP48V60RT3U (no limit) external battery packs (external battery configurations require Tripp Lite's [External Battery Configuration Software](#))
- LCD interface reports operating mode plus 10 selectable screens of UPS data (Input voltage, Input frequency, Output voltage, Output frequency, Load percentage, Load kVA, Load kW, Battery charge percentage, Battery voltage and Minutes runtime)
- LCD interface also supports 9 screens of advanced UPS configuration, setup and information options (Output voltage, Output frequency, Frequency regulation, Bypass range, Economy mode, Audible alarm, Overload alarm, External battery, Display IP address)

- Single line TEL / Network surge suppression
- Electronic bypass maintains utility output during a variety of UPS fault conditions
- Battery independent restart ensures automatic UPS power-up without user interaction after lengthy power outages, even when batteries are expired and require replacement
- Frequency regulation / conversion mode offers generator-compatible frequency correction or conversion of frequency from 50 to 60Hz or 60 to 50Hz
- Built-in USB, RS-232, contact-closure and optional SNMPWEBCARD accessory monitoring options
- HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- Included PowerAlert UPS monitoring software

Specifications

OUTPUT	
Output Volt Amp Capacity (VA)	2200
Output kVA capacity (kVA)	2.2
Output Watt Capacity (watts)	1800
Output kW capacity	1.8
Output power factor	0.82
Output Capacity Details	ON LINE MODE: Maximum output capacity ratings are reduced for some nominal voltage settings (127/120V 1800 watts, 115V 1620 watts, 110V 1530 watts, 100V 1440 watts). FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulation / conversion mode (127/120V 1260 watts, 115V 1134 watts, 110V 1071 watts, 100V 1008 watts).
Crest Factor	3:1
Nominal Output Voltage(s) Supported	100V; 110V; 120V; 127V
Nominal Voltage details	120V default
Frequency compatibility	50 / 60 Hz; Supports 50 to 60 Hz and 60 to 50 Hz conversion
Frequency compatibility details	ON LINE MODE: Output frequency is automatically configured to match nominal input frequency on startup; Output matches input frequency when +/-5Hz of nominal; Output is regulated to +/-0.05Hz when input frequency exceeds +/-5Hz of nominal. UPS switches to battery mode when input frequency is below 40Hz or above 70Hz. FREQUENCY REGULATION / CONVERSION MODE: Output is regulated to +/-0.05Hz of selected output frequency when input is 40 to 70Hz; UPS switches to battery mode when input frequency is below 40Hz or above 70Hz. BATTERY MODE: Output is regulated to +/-0.05Hz of selected nominal.
Output voltage regulation (line mode)	+/- 2%
Output voltage regulation (Economy line mode)	+/- 10%
Output voltage regulation (Battery mode)	+/- 3%
Built-in UPS output receptacles	6 5-15/20R outlet(s); 1 L5-20R outlet(s)

Built-in controllable switched load banks	Two switchable three-outlet load banks
Output AC waveform (AC mode)	Pure Sine wave
Output AC waveform (battery mode)	Pure Sine wave
INPUT	
Rated input current (at maximum load)	16A
Nominal Input Voltage(s) Supported	100V AC; 110V AC; 120V AC; 127V AC
Nominal input voltage description	120V factory default
UPS input connection type	5-20P
Input circuit breaker	30A
UPS Input cord length (ft.)	10
UPS Input cord length (m)	3
Recommended Electrical Service	15A 120V
BATTERY	
Full load runtime (minutes)	4.5 min. (1800w)
Half load runtime (minutes)	13 min. (900w)
Expandable battery runtime	Extended runtime supported via optional external battery packs
External battery pack compatibility	BP48V24-2U (limit 1); BP48V60RT-3U (multi-pack compatible)
Expandable runtime description	External battery configurations require the use of Tripp Lite's External Battery Configuration Software, see manual for details
DC system voltage (VDC)	48
Battery recharge rate (included batteries)	Less than 3 hours from 10% to 90%
Replacement battery cartridge (internal UPS battery replacement)	RBC48-SUTWR
Battery Access	Battery access door

Battery replacement description	Hot-swappable, user replaceable batteries
VOLTAGE REGULATION	
Voltage regulation description	Online, double-conversion power conditioning
Overvoltage correction	2% output voltage regulation during overvoltages to 150
Undervoltage correction	2% output voltage regulation during undervoltages to 55V (33% load), 70V (70% load), 100V (100% load)
LEDS ALARMS & SWITCHES	
Front panel LCD display	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, frequency, operating mode, alarm function and a variety of additional options
Alarms	Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions
Alarm cancel operation	Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available
Switches	2 switches control off/on power status and alarm-cancel/self-test operation
SURGE / NOISE SUPPRESSION	
UPS AC suppression joule rating	570
UPS AC suppression response time	Instantaneous
UPS Dataline suppression	1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet
EMI / RFI AC noise suppression	Yes
PHYSICAL	
Installation form factors supported with included accessories	Tower
Primary form factor	Tower
UPS / Power Module dimensions in primary form factor (height x width x depth / inches)	10.2 x 9 x 19.5
UPS / Power Module dimensions in primary form factor (height x width x depth / cm)	25.9 x 22.9 x 49.5
UPS / Power Module weight (lbs)	52.9
UPS / Power Module weight (kg)	24

UPS Shipping dimensions (height x width x depth / inches)	15.2 x 13 x 24
UPS Shipping dimensions (height x width x depth / cm)	38.6 x 33 x 61
Shipping weight (lbs)	58.2
Shipping weight (kg)	26.4
UPS housing material	Steel
Cooling method	Fan
ENVIRONMENTAL	
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius
Relative Humidity	0 to 95%, non-condensing
AC mode BTU / hr. (full load)	684
AC economy mode BTU / hr. (full load)	190
Battery mode BTU / hr. (full load)	1087
AC economy mode efficiency rating (100% load)	97%
Audible Noise	< 50.5 dB at front side 1m
COMMUNICATIONS	
Communications interface	USB (HID enabled); DB9 Serial; Contact closure; EPO (emergency power off); Slot for SNMP/Web interface
Network monitoring port description	Supports detailed monitoring of UPS and site power conditions; DB9 port supports RS232 and contact closure communications
PowerAlert software	Included
Communications cable	USB and DB9 cabling included
WatchDog compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications
LINE / BATTERY TRANSFER	
Transfer time	Zero transfer time (0 ms.) in online, double-conversion and frequency regulation / conversion modes;

Low voltage transfer to battery power (setpoint)	55V (33% load), 70V (70% load), 100V (100% load)
High voltage transfer to battery power (setpoint)	150
SPECIAL FEATURES	
Cold Start (startup in battery mode during a power failure)	Cold-start operation supported
High availability UPS features	Automatic inverter bypass; Hot swappable batteries
Green & high efficiency features	High efficiency economy mode operation; Individually controllable load banks; Schedulable daily hours of economy mode operation
CERTIFICATIONS	
UPS Certifications	Tested to UL1778 (USA); Tested to CSA (Canada); Tested to NOM (Mexico); Meets FCC Part 15 Category A (EMI)
WARRANTY	
Product Warranty Period (Worldwide)	2-year limited warranty
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance

Related Items

Optional Products

Related Model	Description	Qty.
WEXT3-2200-3000	3-Year Extended Warranty - For Smart Line-Interactive and Online Tower or Rack models, 2200-3000VA	1
WEXT5-2200-3000	5-Year Extended Warranty - For Smart Line-Interactive and Online Tower or Rack models, 2200-3000VA or less	1
SNMPWEBCARD	For remote monitoring and control via SNMP, Web or Telnet	1
ENVIROSENSE	Monitors temperature, humidity and contact-closure inputs. (Requires UPS with SNMPWEBCARD, monitored PDU or switched PDU.)	1
RELAYIOCARD	Programmable Relay I/O Card	1
MODBUSCARD	For remote monitoring and control via MODBUS protocol	1
BP48V24-2U	External Battery Pack for UPS System	1
BP48V60RT-3U	External Battery Pack and Cable. 3U, Expandable, Blue 2-Point Connector	1
PDUB20	Single-Phase Hot-Swap PDU, 20A 120V, 2U Horizontal Rackmount, 4 NEMA 5-15R & 4 NEMA 5-15/20R outlets, 2 NEMA 5-20P input plugs	1
PDUMH20NET	Single-Phase Switched PDU, 20A 120V, 1U Horizontal Rackmount, 16 NEMA 5-15/20R outlets, NEMA L5-20P input with 5-20P adapter	1
PDUMH20AT	Single-Phase Auto Transfer Switch / Metered PDU, 20A 120V, 1U Horizontal Rackmount, 16 5-15/20R outlets, 2 L5-20P / 5-20P adapters	1
PDUMH20ATNET	Single-Phase Auto Transfer Switch / Switched PDU 20A 120V, 1U Horizontal Rackmount, 16 5-15/20R outlets, 2 L5-20P / 5-20P inputs	1

PDU1220	Single-Phase Basic PDU, 20A 120V, 1U Horizontal Rackmount, 13 NEMA 5-15/20R outlets, NEMA 5-20P input plug	1
PDUMH20	Single-Phase Metered PDU, 20A 120V, 1U Horizontal Rackmount, 12 NEMA 5-15/20R outlets, NEMA L5-20P input with 5-20P adapter	1
PDUMNV20	Single-Phase Monitored PDU, 20A 120V, 70 in. 0U Vertical Rackmount, 24 NEMA 5-15/20R outlets, NEMA L5-20P input with 5-20P adapter	1
PDUMV20	Single-Phase Metered PDU, 20A 120V, 0U Vertical Rackmount, 28 NEMA 5-15/20R outlets, NEMA L5-20P input with 5-20P adapter	1
PDUMNH20	Single-Phase Monitored PDU, 20A 120V, 1U Horizontal Rackmount, 8 NEMA 5-15/20R outlets, NEMA L5-20P input with 5-20P adapter	1
PDUMV20NET	Single-Phase Switched PDU, 20A 120V, 0U Vertical Rackmount, 24 NEMA 5-15/20R outlets, NEMA L5-20P input with 5-20P adapter	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at www.tripplite.com/en/products/model.cfm?variables.txtModelID=5340.

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.