

## APC J Type Power Conditioners with Battery Backup

Pure sine-wave battery backup and guaranteed surge protection deliver pure, uninterrupted power for high performance AV, home security, and home theater systems.







Never let a power disruption interrupt your life again.

During a power disturbance, the APC J Type allows you to:

- Eliminate interruptions
- Continue DVR recordings
- Protect hard drives and display bulbs
- Monitor home automation and security systems





## APC J Type Power Conditioners with Battery Backup

Product Details	J10BLK	J15BLK	J25B	J35B
Input Voltage	120 V	120 V	120 V	120 V
Input Connection	NEMA 5-15P	NEMA 5-15P	NEMA 5-15P	NEMA 5-15P
Rated VA Capacity	1,000 VA	1,500 VA	1,500 VA	1,500 VA
Rated Watt Capacity	600 W	865 W	865 W	865 W
Output Connections	(12) NEMA 5-15R Battery Backup		(6) NEMA 5-15R Battery Backup, (2) NEMA 5-15R Surge Protected	
Coax Protection	3 Pair	3 Pair + Splitter	1 Pair	1 Pair
Tel/DVR/SAT/DSL Protection	2 Pair	2 Pair	None	1 Pair
Outlet Bank Features	Sequenced Turn On/Off		N/A	Master and Controlled by Master
Estimated Runtime at Half-Load	18 Min	14 Min	12 Min	20 Min
Estimated Runtime at Full-Load	6 Min	4 Min	4 Min	6 Min
Communication	LCD Status and Control Console			
Product Warranty	2 Years		3 Years	
Lifetime Equipment Protection Policy	\$750,000 Lifetime		\$350,000 Lifetime	

The J10BLK and J15BLK models reduce electromagnetic and radio frequency interference (EMI/RFI). Each filter bank is electrically isolated from each other to prevent noise generated by one component from polluting other connected components.

The J35B offers boost and trim automatic voltage regulation (AVR) which eliminates voltage fluctuations as a source of AV signal degradation and component power-supply stress without using the internal battery.



J15BLK



J35B



